

**Celadon Inc.**

**RCV-5000 IR to RS-232 ASCII Output Table**

**Device: AMX/ Autopatch PrecisLT AVS-PL-0808-345 8X8 Matrix Switcher**

Infrared Remote Control: Philips PRONTO (CCF)

Infrared Code Format: NEC - Device ID: 7B02

Infrared Pronto Data File(s): RCV5000a.CCF

Infrared Receiver: Celadon RCV-5000 Infrared to RS-232 Receiver

RCV-5000 Data File: autopatch1\_r.hex

Data: 9600 Baud, 8, N, 1, ASCII Output

Standard Transmit and Receive pinout

Matrix Switcher Function	Pronto Button	RCV-5000 Output
Change	0	C
Disconnect	1	D
Status	2	S
Level	3	L
0	4	0
1	5	1
2	6	2
3	7	3
4	8	4
5	9	5
6	10	6
7	11	7
8	12	8
9	13	9
Input	14	I
Output	15	O
Space	16	" "
Take	17	T
Exit	18	X

Celadon, Inc.

50 Mitchell Blvd.

San Rafael, CA 94903

Sales: (707) 648-1098

Main Tel: (415) 472-1177

Main Fax: (415) 472-1179

sales@celadon.com